

Broadband, Multirange Directional RF Wattmeter Model 81060

[\[Printer Friendly\]](#) [\[Product Flyer\]](#) [\[Manual\]](#)

Features

- *Non-Removable Broadband Element*
- *Shock Mounted "Taut Band" Meter*
- *4-1/2" Mirrored Scale*
- *Quick Match Connectors*
- *Internal 7/8" Line Section*
- *Gold Plated Element*
- *Two Year Limited Warranty*



[\[View Larger\]](#)

Description

With the Model 81060 Directional Wattmeter you can now measure RF power in 50-Ohm coaxial cable and transmission lines without the need for additional plug-in elements.

Model 81060 comes complete with the same 4-1/2" taut band meter movement, Quick Match RF Connectors, and precision line section that are used in our Model [81000-A](#) and [83000-A](#) Wattmeters.

These features plus a special non-removable Broadband Element allow full-scale power measurement on any one of 5 selectable ranges of 15, 50, 150, 500, and 1500 watts across a frequency range of 25 to 1000 MHz.

Versatile and reliable, the Model 81060 is also easy to use. Simply connect the Wattmeter between the transmitter and the antenna or dummy load, select the appropriate power range on the 5 position switch, and read the power directly on the mirrored backed meter when the frequency is between 100 and 1000 MHz. Below 100 MHz, multiply the meter reading by the correction factor found on the chart on the back of the Wattmeter.

The use of a rugged shock mounted meter with a mirror-backed scale along with superior taut band technology, provides reliable and accurate readings, and also satisfies both the US Navy and Canadian standards for bounce and vibration. This is your assurance of complete accuracy.

Your confidence in the quality and dependability of the Model 81060 Wattmeter is assured with the Coaxial Dynamics Two Year Limited Warranty.

Specifications

Power Ranges	15, 50, 150, 500 and 1500 watts full scale (500 watts maximum from 800 to 1000 MHz)
Frequency Range	25 MHz to 1000 MHz
VSWR	1.08 max. from 25 to 512 MHz (with UHF female connectors) 1.12 max. from 512 to 1000 MHz (with UHF female connectors)
Insertion Loss	0.10 dB max. from 25 to 512 MHz (with UHF female connectors) 0.15 dB max. from 512 to 1000 MHz (with UHF female connectors)
Accuracy	25 to 100 MHz, $\pm 7\%$ of full scale using corrections chart 100 to 512 MHz, $\pm 6\%$ of full scale, no correction required 512 to 1000 MHz, $\pm 7\%$ of full scale, no correction required
Element	Non-Removable Broadband (25 to 1000 MHz, 1500 watts max.) rotatable for forward and reflected power measurements
Impedance	50-Ohms
RF Connectors	Type UHF Female standard (see note below)
Dimensions (H x W x D)	7.3 in. (18.5 cm) x 5 in. (12.7 cm) x 4 in. (10.2 cm)
Weight	3.8 lbs. (1.72 kg)
Case Finish	Textured Blue Polyurethane Enamel
<i>Note: Other Quick Match Connectors are available.</i>	

[general documents/SUPPLIERS/COAXIAL/specs for online catalogue/Directional Wattmeters/footer.htm]