


WAVEGUIDE SMA ADAPTERS COVER FLANGE

P/N	FREQ ghz	A	B	C	D	E	F	G	H	I	J	M
					WG INNER	WG INNER	FLANGE L	FLANGE H-H	FLANGE W	FLANGE H-H	DIA	
28AC206	26.5-40.0	0.52	0.52	0.35	0.28	0.14	0.75	0.5	0.75	0.53	0.116	0.19
34AC206	22.0-33.0	0.62	0.54	0.4	0.34	0.17	0.88	0.64	0.88	0.67	0.116	0.19
42AC206	18.0-26.5	0.62	0.54	0.4	0.42	0.17	0.88	0.64	0.88	0.67	0.116	0.19
62AC206	12.4-18.0	0.79	0.62	0.5	0.622	0.311	1.312	0.994	1.312	0.906	0.147	0.25
75AC206	10.0-15.0	0.9	0.68	0.55	0.75	0.375	1.5	1.04	1.5	1.122	0.144	0.25
90AC206	8.2-12.4	1.02	0.69	0.62	0.9	0.4	1.63	1.22	1.63	1.28	0.169	0.25



S. M. ELECTRONICS
 FAIRVIEW, TX 75069 WWW.SMELECTRONICS.US

TITLE

WG-COAX ADAPTERS

SIZE	CAGE CODE	DWG NO	REV
A	3FKR5		A
SCALE	SHEET		